

Product Overview

716P Manual Pull Station is a high quality non-toxic die-cast manual pull station. Low profile design and smooth edges offer an attractive yet functional design. All components are pre-painted or have plated surfaces to inhibit corrosion. Electrically the 716P Manual pull station is unbeatable with 10 Amp snap action switch offered in all possible contact arrangements (including gold contacts). The 716P pull station can be used with or without a break glass rod, with replacement requiring no special tools.

Features

- Lift and pull
- Break glass cover
- Weather and Explosion proof versions(optional)
- All stations offer hex screw or key lock access.

Construction Material

- Painted Die Cast Housing.
- 14 Ga plated steel black plate.
- Corrosion Inhibited surfaces.
- Terminal block (4 Position)
- Single Gang Mounting
- 10 A , 120VAC snap Action Switch (S.P.S.T.)

Specification

Electrical

Switch : 10A@120VAC

Dimensions

Station Width : 3.200 in
 Length : 4.750 in
 Depth : 0.875 in

Weight : 15.5 oz / 420 grams
 Mount : Single gang



Ordering Information

MODELS	DESCRIPTION	COLOR
716P1TLP(R)	Manual Pull station Dual Action	RED

www.cagsfiresystem.in

